



PV Microinverter BENY

BYM500 / BYM550 / BYM600



Type Approved
Safety
Regular Production
Surveillance
www.tuv.com
ID 111261691

Datasheet

ZHEJIANG BENYI NEW ENERGY CO.,LTD.

CHONGJIANG RD, WENZHOU DAQIAO INDUSTRY PARK, BEIBAIXIANG TOWN, YUEQING, WENZHOU CITY, ZHEJIANG PROVINCE, CHINA
TEL: +86-577-57177008 FAX: +86-577-57177007

www.benyi.com

© 2014 BENYI NEW ENERGY CO., LTD. All rights reserved.

This document contains trade secrets and/or confidential information of BENYI NEW ENERGY CO., LTD. It is the property of BENYI NEW ENERGY CO., LTD. It is illegal to copy or otherwise disclose this document without the express written consent of BENYI NEW ENERGY CO., LTD.

All trademarks and registered trademarks are the property of their respective owners.



VERSION: 20231018-01

WWW.BENY.COM

BENY



Description

With the maximum output power of 520/570/600VA, BENY BYM500/550/600 microinverter connect to 1 module and enable module-level maintenance and management of the PV station by monitoring power generation of each module.

Module-level data can be uploaded to the monitoring platform via BENY data transfer units through PLCC/Wi-Fi.



Maximum output power up to 520VA/570VA/600VA channel, adapted to 60~75-cell or 120~150 half-cell PV modules



Static MPPT efficiency 99.80%



High reliability, IP67 (NEMA 6) enclosure

SAFETY Low DC voltage, and invisible.	QUALITY Components selected from world-class brands.	OPTIMIZATION High efficiency for each module	PARALLEL INPUT 18A continuous input
FLEXIBILITY Adapts to any system size and optimizes space.	PLUG & PLAY AC BUS design no SPoF	25 YEARS 30-year design life up to 25-year warranty	SMART Module-level online smart monitoring.

Input Data (DC)

Model	BYM500	BYM550	BYM600
Recommended input power (Single)	(STC) 400~700+ Wp , 60 ~75-cell/120~150 half-cell		
Recommended input power (Dual)	(STC) (300~450 Wp) x 2, 72~75-cell/144~150 half-cell (NMOT) Vmp>34V and Imp<12A		
MPPT voltage range	24V~50V		
Operating voltage range	16V~60V		
Maximum input voltage	60V		
Max. short circuit current	20A	24A	
Max. input current	18A		20A

Output Data(AC)

Rated output power	500W	550W	600W
Maximum output power	520VA (Vac>230,Vmp>34)	570VA (Vac>230,Vmp>35)	600VA (Vac>220,Vmp>33)
Rated voltage(range)	230V(176V~265V)		
Rated frequency(range)	50Hz/60Hz (46.5Hz~62Hz)		
Maximum continuous output current	2.27A	2.5A	2.73A
Maximum harmonic distortion	<4%		
Power factor	>0.99 (Default)		
Maximum connection number in one string	8 units (24A circuit breaker, 12AWG cable)		

Efficiency	
Peak efficiency	96.5%
MPPT efficiency	>99.8%
Night power consumption	<100mW
Other Parameters	
Communication method	PLCC/Wi-Fi [Optional]
Safety protection	Class I
Enclosure rating	IP67
Operating temperature	-40°C to +70°C
Storage temperature	-40°C to +85°C
Relative humidity	0-98%
Transformer design	High frequency transformer, Electrical isolated
Overshoot class	OVC III (AC), OVC II (PV)
Warranty period	10 / 25years (Optional)
Dimensions(L*W*H mm)	210*230*34
Weight(kg)	2.39
Safety regulations	IEC/EN 61000-6, CISPR11+A1+A2, IEC/EN 62109-1/2, EN 50549-1:2019 VDE-AR-N 4105:2018/DIN VDE 0124:2020, AS 4777.2:2020, INMETRO, UTE C15-712-1/DIN VDE 0126/VFR 2019, 698, CEI 0-21:2020, NC RFG, NTS DAKKS.

Monitoring Device

Communication with BENY microinverters through PLCC/Wi-Fi enables users to manage the systems in a smart digital way.

